

POLE A

SIGNAL HEAD					POLE BASE	CONDUIT		CONTROLLER
HEAD NUMBER	FUNCTION	CON #	WIRE COLOR	TERMINAL	CON #	WIRE COLOR	FUNCTION	
3 & 2	RED (RIGHT)	1	BLACK	[Terminal Diagram]	1	BLACK	PH 1 RED	
	SIGNAL COMMON	2	WHITE		2	WHITE	SIGNAL COMMON	
	RED (LEFT)	3	RED		3	RED	PH 5 RED	
	SPARE	4	GREEN		4	GREEN	PH 4 WALK	
	YELLOW	5	ORANGE		5	ORANGE	PH 6 YELLOW	
1	SPARE	1	BLACK		6	BLUE	PH 4 DONT WALK	
	SIGNAL COMMON	2	WHITE		7	BLACK/ WHITE	P. CALL	
	DON'T WALK	3	RED					
	WALK	4	GREEN					
	SPARE	5	ORANGE					
P6-2CS	PUSH	1	BLACK					
	BUTTON	2	WHITE					

POLE B

SIGNAL HEAD					POLE BASE	CONDUIT		CONTROLLER
HEAD NUMBER	FUNCTION	CON #	WIRE COLOR	TERMINAL	CON #	WIRE COLOR	FUNCTION	
4 & 5	RED (RIGHT)	1	BLACK	[Terminal Diagram]	1	BLACK	PH 1 RED	
	SIGNAL COMMON	2	WHITE		2	WHITE	SIGNAL COMMON	
	RED (LEFT)	3	RED		3	RED	PH 5 RED	
	SPARE	4	GREEN		4	GREEN	PH 4 WALK	
	YELLOW	5	ORANGE		5	ORANGE	PH 6 YELLOW	
6	SPARE	1	BLACK		6	BLUE	PH 4 DONT WALK	
	SIGNAL COMMON	2	WHITE		7	BLACK/ WHITE	P. CALL	
	DON'T WALK	3	RED					
	WALK	4	GREEN					
	SPARE	5	ORANGE					
P6-2CS	PUSH	1	BLACK					
	BUTTON	2	WHITE					

DIRECTION	BLOCK #	PHASE			
		Ø4	Ø1	Ø6	Ø5
Ø1 & Ø6 ROW	A1	DW	SIGNAL DARK		
Ø1 & Ø6 CL	A2	DW	DARK	Y	DARK
Ø4 ROW	A3	W	R	DARK	R
Ø4 CL	A4	FDW	FLASH R	DARK	FLASH R

